

# METHOD OF REGULATING SMART CARD USAGE AND/OR CONCESSION ELIGIBILITY IN A SMART CARD SYSTEM

5

## Field of the Invention

The present invention relates generally to a method of regulating smart card usage and/or concession eligibility in a smart card system.

## Background of the Invention

10 Most smart card systems employ a stored value concept. This means that the smart card has the electronic value stored in its internal memory. These smart cards can be purchased with electronic cash pre-loaded. Electronic cash value can be added to these smart cards at kiosks by the cardholder via credit cards, debit cards, cash, etc. These kiosks are generally referred to as add value stations. The  
15 disadvantages to these systems are that they require convenient and multiple add value stations available to the cardholder in order to gain acceptance. Moreover, there is added cost to the system owner to purchase, install and maintain these stations, as well as the credit, debit and cash handling costs. The reloading of these smart cards is left at the discretion of the cardholder, that is to say that if the  
20 initial value of the purchased smart card is used up and the cardholder cannot access an add value station, the smart card system will simply deny access to the system unless there is the sufficient electronic value stored on the smart card.

In the event that a non-anonymous, stored-value smart card is lost or stolen, the cardholder must report the smart card to a customer service center and  
25 a replacement card is sent to the cardholder. A disadvantage to this model is that once a smart card is reported lost or stolen, the smart card is permanently inactivated even if the smart card is subsequently found since the value of the lost/stolen card has been duplicated on the replacement card. In anonymous stored-value smart cards, there is nothing that can be done to reimburse the  
30 cardholder for the lost value on the lost/stolen smart card since there is no link between the smart card and the cardholder. In non-stored value smart card

systems, where the smart card is linked to a cardholder's bank account to make automatic deductions, there are numerous business scenarios where a card may be deemed temporarily ineligible to participate in the system. In these systems, permanently disabling the smart card would greatly inconvenience the cardholder and represent a significant cost to the system operators/owners.

Thus, there exists a need for regulating smart card usage in smart card systems without burdening the cardholder with constant monitoring and replenishing the value on the card and without having the system owners bear unnecessary costs.

### **Brief Description of the Drawings**

A preferred embodiment of the invention is now described, by way of example only, with reference to the accompanying drawings in which:

FIG. 1 illustrates a diagram of a smart card system for regulating smart card usage in accordance with the preferred embodiment of the present invention;

FIGS. 2A and 2B illustrate a flow chart depicting the algorithm used to determine the eligibility of a smart card to participate in the system in accordance with the preferred embodiment of the present invention;

FIG. 3 illustrates a bounce diagram for disabling a smart card in accordance with the preferred embodiment of the present invention;

FIG. 4 illustrates a bounce diagram for enabling a smart card in accordance with the preferred embodiment of the present invention;

FIG. 5 illustrates a diagram of a smart card system for regulating concession eligibility in accordance with an alternative embodiment of the present invention;

FIGS. 6A and 6B illustrate a flow chart depicting regulation of concession eligibility in accordance with the alternative embodiment of the present invention; and

FIG. 7 illustrates a bounce diagram of regulating concession eligibility in accordance with the alternative embodiment of the present invention.

### **Detail Description of the Preferred Embodiment**

As shown in FIG. 1, a smart card system 100 comprises front office components and back office components. A discussion of the front office components will be discussed first. Examples of front office components include the smart card and the card acceptance location 110. The card acceptance location 110 comprises a card reader that reads the smart cards when presented to it, and memory in which to record transactions and store operating and card information. The card acceptance location 110 may be mobile/portable location (e.g., bus, train, taxi, etc.), and the reader may be a hand held device or semi-permanent device installed at the card acceptance location 110. When the card acceptance location 110 is mobile/portable, it is typically connected to the back office components in an off-line mode. The card acceptance location 110 may also be a fixed location, such as retail stores, and connected to the back office components in an on-line mode. The card acceptance location 110 is responsible for creating smart card transactions and forwarding these transactions to the back office components for processing, including settlement and clearing of these transactions.

Presentation of a smart card to a card acceptance location 110 allows the card acceptance location 110 to power the smart card and communicate securely with it at a set frequency. During this communication, commands and responses are securely passed back and forth between the smart card and the card acceptance location 110. During the initial stages of communication, the smart card and the card acceptance location 110 identify each other in an unsecure manner. This initial identification allows the card acceptance location 110 and the smart card to quickly identify each other as components on the same system 100, as well as have the opportunity to check the component status of each device. After such identification, a secure verification of the smart card and card acceptance location 110 is performed. This verification process is commonly known as a three pass mutual authentication. The three pass mutual authentication is more time

consuming than the initial identification process, and along with the secure data communication method, is responsible for a large portion of the total transaction time. Once the mutual authentication has successfully completed, specific smart card application commands are performed. For example, the smart card transaction is recorded in a transaction log file on the smart card and a transaction record is generated, stored in the card acceptance location's memory, and later forwarded to the back office components for processing.

The smart card is known to the system 100 by a unique identification identifier ("UID") stored on the smart card in electronic form. This UID is electronically linked in the smart card system to the cardholder. Based on this identification, the concept of a hot list is introduced in accordance with the present invention. The hot list is a collection of smart card UIDs that the card acceptance location 110 must take an action on when the UID of the presented smart card is matched with an entry on the hot list. In the preferred embodiment of the present invention, the hot list is stored locally at the card acceptance location 110 and updated in a batch format by the back office components on a periodic basis, e.g., hourly, daily, weekly, monthly, etc. Preferably, the hot list comprises black list items and green list items. The black list items represent smart card UIDs that should be disabled when the smart card is presented to any of the card acceptance locations 110 in the smart card system 100, thereby denying access to the system 100. The green list items represent smart card UIDs that have previously been deemed ineligible to participate in the system, placed on the black list and disabled, and is now ready to be re-enabled when the smart card is presented to any of the card acceptance locations 110, thereby re-gaining access to the system 100.

In accordance with the preferred embodiment of the present invention, a smart card UID is added to the hot list as a black list item, for example, when the smart card is reported lost or stolen. Another example is when the cardholder's account that the smart card is linked to falls below a predetermined threshold balance or is delinquent. Typically, the predetermined threshold balance is

established by a set of criteria determined by the owner of the smart card system, but can also be established by other means.

With respect to green list items, a smart card UID is added to the hot list as a green list item, for example, when the smart card that was previously reported as  
 5 lost or stolen is found. Another example is when the cardholder's account balance has been replenished, thus meeting or exceeding the predetermined threshold balance of the owner of the smart card system. The advantage of this system is that it allows a customer to quickly resume smart card transactions after he/she was temporarily deemed ineligible from participating.

10 In accordance with the preferred embodiment of the present invention, the back office components may limit the sizes of the black list and green list to fit the memory of a card acceptance location. It may limit the list sizes by geographic location of the card acceptance location, the value of a card with a particular UID, the computed potential fraud value of the card, or any combination of these and  
 15 other methods.

Now lets turn the discussion to the back office components. Examples of the back office components are a central processing component 120, a financial processing component 130, a customer service component 140, and a smart card processing component 150. The smart card system 100 may also comprise a  
 20 configuration manager 160 and a card reader interface device 170. The central processing component 120 is responsible for consolidating transactions from service providers. In certain non-stored value smart card systems, the central processing component 120 may rate the transaction. The central processing component 120 may also have the responsibility of monitoring transactions for  
 25 possible anomalies that result from fraudulent card usage. For example, the central processing component 120 will detect when two transactions occur at the same time, with the same smart card UID, at different locations. As such, the central processing component 120 assists in fraud protection for the cardholder.

The financial processing component 130 is responsible for settling the  
 30 transactions between the cardholders and the service providers. In stored value

systems, the financial processing component 130 tallies all transactions belonging to a specific service provider and transfers the correct funds to the service provider. In non-stored value systems, the financial processing component 130 tallies all transactions owed to a specific service provider by a respective  
5 cardholder, deducts the amounts from the respective cardholder's bank account, and transfers the equivalent amount to the service provider to settle the transaction. Thus, the smart card system 100 in accordance with the preferred embodiment of the present invention is based on the automatic revaluation of linked financial accounts. That is to say that there is no electronic cash value  
10 stored on the smart card. The cardholder provides the system with a bank account number that funds are initially drawn out of and when the balance of the smart card account gets to a preset low level, the system automatically initiates a transfer of funds from the cardholder's bank account to the smart card account maintained by the smart card system owner. The financial processing component  
15 130 must constantly monitor the financial status of the cardholders to ensure that they are able to pay for their accrued transactions. An advantage of this system to the system owner is that there is no add value stations required. Additionally, there is no burden on the cardholder to reload electronic cash, thus making participation in the system un-interrupted.

20 The customer service component 140 of the smart card system 100 is responsible for interfacing with the cardholder in handling questions, complaints, and issues. One specific function of the customer service component 140 is to allow the cardholders to report the physical status of their smart cards should the physical status change. For example, the cardholders will report to the customer  
25 service component 140 that their smart card is lost, stolen or found.

The smart card processing component 150 of the smart card system 100 is responsible for monitoring the conditions that would make a smart card eligible or ineligible to participate in the system 100 based on the criteria of the service providers, system operators, system owners, or any combination thereof. In the  
30 preferred embodiment of the present invention, the smart card processing

component 150 monitors the fraudulent smart card usage data from the central processing component 120, the cardholder financial status data from the financial processing component 130, and the smart card physical status from the customer service component 140, in determining the eligibility of the smart card to participate in the system 100. From this information, the smart card processing components 150 builds the hot list.

The configuration manager 160 combines the generated hot list with other related operational data and forwards the data to a card reader interface device 170 (e.g., a central computer) for which that data is intended.

The card reader interface device 170 communicates with numerous card acceptance locations 110 in the system 100. All card acceptance locations 110 connected to the card reader interface device 170 may or may not share common operational data, including the hot list. The card reader interface device 170, however, ensures transmission of the correct operational data to the respective card acceptance locations 110. The card acceptance locations 110 are mapped to a card reader interface device 170 based on geographical proximity to the card reader interface device 170, as well as other factors, such as the service providers who are using the card acceptance locations 110, the system operators who are maintaining the card acceptance locations 110, and the system owners who own the card acceptance locations 110. Notwithstanding the above, security reasons, however, may dictate that card acceptance locations 110 in different retail stores may not be mapped to a single card reader interface device 170.

On either a periodic basis, or on demand, the smart card processing component 150 of the system 100 builds the hot list and forwards the hot list to the configuration manager 160 for inclusion with other operational data to be sent to the card acceptance locations 110 via the card reader interface device 170. On a timed basis, or whenever the card acceptance location 110 comes on-line, the card reader interface device 170 forwards the operational data, which includes the hot list, to the intended card acceptance locations 110. Preferably, the card acceptance locations 110 acknowledge successful receipt of the hot list and other

operational data, and no further attempts are made by the system 100 to transmit the lists to these particular card acceptance locations 110 until updated operational data is generated. Each card acceptance location 110 stores the most recent operational data in its memory.

5           Now that each card acceptance location 110 has locally stored operational data, the card acceptance location 110 can operate in a standalone mode to create smart card transactions for smart cards presented to it for transaction purposes. Smart card transactions include, but are not limited to, debit transactions, credit transactions, disable transactions and enable transactions.

10           In operation, when a smart card is presented to a card acceptance location 110, the card acceptance location 110 checks the state of the smart card during initial identification. In the preferred embodiment, a status bit in the system file indicates the state of the smart card. The smart card has a file system that has critical files stored on it to interact with the card acceptance location 110 to create  
15 a transaction record. The transaction log file is one of these critical files. Additionally, critical data from the system file is sent to the card acceptance location 110 during the initial communication between the card acceptance location 110 and the smart card, prior to the mutual authentication stage. This data quickly indicates to the card acceptance location 110 the status of the smart  
20 card prior to the secure and more time consuming mutual authentication process. Usage of both the system file and the transaction log file is used to comprise a solution that would allow a card acceptance location 110 to disable and/or enable a smart card. Thus, the card acceptance locations 110 disable and enable smart cards based on the status information of the smart card and the hot list stored  
25 locally.

          If the smart card status bit indicates that the smart card is presently enabled, the card acceptance location 110 checks the black list items in the hot list for a match. If a match is found, the card acceptance location 110 sets the status bit to indicate that this smart card is disabled and blocked from further use until  
30 this condition is cleared. Further, the card acceptance location 110 instructs the



smart card to block all access to the transaction log file until further notice. The card acceptance location 110 creates a disable transaction and forwards it to the SCPS 150 to purge the entry from the black list items in the hot list. The entry is purged from the hot list once the card acceptance location 110 takes action on the smart card in order to keep the size of the hot list to a minimum, and prevents the list from growing without bound. If a match is not found, the card acceptance location 110 performs the desired transaction. Depending on the application, the card acceptance location 110 may generate audio and/or visual indicators indicating that that transaction was successfully completed. The card acceptance location 110 forwards the transaction record to the back office components for further processing, settlement and clearing. If in the process of performing the transaction, the card acceptance location is blocked by the smart card from accessing its transaction log file (i.e., the status bit and the blocking status are inconsistent), a fraud transaction is created and transmitted to the back office components, the status bit is set to disabled, and the cardholder is denied service/product. This is in the unlikely event that a user will be able to independently read the file system, defeat the mutual authentication, and change the status bit, in an attempt to re-enable the smart card.

If the smart card status bit indicates that the smart card is presently disabled, the card acceptance location 110 checks the green list items on the hot list. If a match is found, the card acceptance location 110 changes the status bit in the system file and instructs the smart card to unblock access to the transaction log file. The card acceptance location 110 creates an enable transaction and performs the desired transaction. Depending on the application, the card acceptance location 110 may generate audio and/or visual indicators indicating that the transaction was successfully completed. The card acceptance location 110 forwards the transactions to the back office components for processing and purging the entry from the green list items on the hot list. If in the process of unblocking the smart card the card acceptance location finds that the smart card has already been unblocked (i.e., the status bit and the blocking status are

inconsistent), a fraud transaction is created and transmitted to the back office components, the card is blocked and the status bit is set to disabled. The cardholder will be denied service/product at this point. Again, this is in the unlikely event that a user was able to independently defeat mutual authentication and unblock the smart card, in an attempt to re-enable the smart card. If a match is not found, the card acceptance location 110 indicates that this smart card is invalid for transaction use. Preferably, the card acceptance location 110 generates audio and/or visual indicators indicating that this was a failed transaction, thus denying access to the system 100.

10 In accordance with the preferred embodiment of the present invention, all card acceptance locations 110 in the smart card system 100 need not be synchronized with the same version of the hot list nor must they behave identically to each other. Further, the black list items and the green list items are preferably stored in separate files in order to minimize the number of entries that each UID of the presented smart card has to be compared to.

15 FIGS. 2A and 2B illustrate a flow chart depicting events of the preferred embodiment for regulating smart card usage (e.g., disablement and enablement of smart cards), or in other words, the algorithm used to determine the eligibility of a smart card to participate in the system 100. Processing begins 201 in the back office system 200, where a computer and database system monitors 202 the usage parameters of each smart card. The back office system 200 determines 203 whether a particular smart card should be disabled. The particular reasons for disabling a smart card in the system may be that the cardholder has exceeded the financial limits prescribed for card usage, that the cardholder has reported the card lost or stolen, or any other reason codified in the business rules of the particular system.

20 If the back office system 200 determines that the smart card should be disabled, it checks 204 to determine whether the smart card is currently enabled. If the smart card is not currently enabled, as determined from records in the back office's database, the back office system 200 proceeds to a combination step 210.

30

If the smart card is currently enabled, the back office system 200 determines 205 which card acceptance location(s) 213 it should associate with the card in order to transmit to the appropriate card acceptance location(s) 213 a list containing which cards should be disabled. The back office system 200 records 206 the UID of the  
5 smart card on the disable list(s) of the card acceptance location(s) 213 it determined in 205, and then combines 210 disable and enable lists with other operational data.

If the back office system 200 determines that the smart card should not be disabled 203, it determines whether the smart card is already currently disabled  
10 207, as represented in the database of the back office system 200. If the smart card is not disabled, processing proceeds at the combination step 210. If the smart card is disabled, the back office system 200 determines 208 which card acceptance location(s) 213 it should associate with the card in order to transmit to the appropriate card acceptance location(s) 213 a list containing which cards  
15 should be enabled. The back office system 200 records 209 the UID of the smart card on the enable list(s) of the card acceptance location(s) 213 it determined in 208, and then combines 210 disable and enable lists with other operational data.

During the combination step 210, the back office system 200 may determine that the combined enable list(s) and disable list(s) exceed the memory  
20 size of the target card acceptance location(s). If this occurs, the back office system may limit the sizes of the black list and green list to fit the memory of a card acceptance location(s). It may limit the list sizes by geographic location of the card acceptance location, the value of a card with a particular UID, the computed potential fraud value of the card, or any combination of these and other  
25 methods. In computing the potential fraud value of a card, the back office system 200 may take into account the associated debit or credit value of a card, the recentness of use of the card after the cards being reported lost or stolen, the remaining transaction value of the card, or any combination of these or other values associated with the card, combined with parameters representing the  
30 business rules of the system 100 operator.



status bit indicates 216 that the smart card is not disabled, and the card acceptance location 213 determines 217 that the smart card file system is not blocked, then the card acceptance location 213 determines 218 whether the UID of the smart card is present on the disable list. If the UID of the smart card is not 218 on the  
5 disable list, the card acceptance location 213 allows 228 the requested service and creates a corresponding service transaction. If the UID of the smart card is 218 on the disable list, the card acceptance location 213 sets 219 the smart card's disable bit and commands the smart card to block the smart card file system. The card acceptance location 213 creates 220 a corresponding disabled transaction and  
10 disallows 221 the requested service.

When the card acceptance location is at the end of its service period 229, it transmits all service, enable and disable transactions 230 to the back office system 200, and ends 231 the cycle. At the back office system, transmitted transactions are used to purge 232 the enable and disable lists of smart card UIDs. If the card  
15 acceptance location is not at the end of its service period 229, it continues to check 215 the status of presented smart cards.

FIGs. 3 and 4 illustrate bounce diagrams in accordance with the preferred embodiment of the present invention. FIG. 3 illustrates the bounce diagram for disabling a smart card, and FIG. 4 illustrates the bounce diagram for enabling a  
20 smart card. With reference to the above description and FIGs. 1 and 2, FIGs. 3 and 4 are self-explanatory and will not be described in detail.

An alternative embodiment of the present invention is illustrated in FIG. 5. In the alternative embodiment, the front office components are responsible for updating the smart cards with any cardholder concessions and loyalty programs  
25 that should be placed on the smart cards. The back office components are responsible for monitoring the concession and/or loyalty program eligibility as well as apply the concession and loyalty programs to smart card transactions.

In accordance with the alternative embodiment of the present invention, the back office components may comprise a cardholder account processing system  
30 ("CHAPS") 310, an account processing system ("APS") 320, a SCPS 330, a

transaction processor 340, and a configuration manager 350. In the alternative embodiment, the CHAPS 310 is the back office server component responsible for monitoring the conditions that would make a smart card user eligible or ineligible for concessions and loyalty programs, as defined by the service providers, smart card system operators, and/or smart card system owners. For example, the CHAPS 310 automatically grants senior discount concessions to cardholders that reach a pre-determined age by monitoring the current age of the cardholder. The CHAPS 310 may also monitor customer concession status. The CHAPS 310 is dedicated to monitoring the variable number of events and statuses that should be considered in determining the cardholder's concessions in the system 300. In some smart card systems, there may be multiple service providers (retailers, transit systems, etc.) that incorporate card acceptance locations as payment collection points in their businesses. Each service provider has well defined criteria determining concession and loyalty program eligibility in the smart card system. In addition, there may be separate smart card system operators and smart card system owners that define their own loyalty programs to reward smart card usage within their system. The CHAPS 310 monitors all the necessary criteria set by the service providers, system operators, and/or system owners to regulate concession and loyalty program eligibility.

The APS 320 is responsible for monitoring the conditions that would make an account owner eligible/ineligible for loyalty programs that are available to the account owner, as defined by the service providers, smart card system operators, and/or smart card system owners. The account owner has financial responsibility for the smart cards that are issued to his/her account. The account owner does not necessarily have to be the cardholder (e.g., a parent paying for the service (e.g., public transportation) for his/her child (cardholder), etc.).

The SCPS 330 is responsible for building the cardholder concession and loyalty lists that must be transmitted to the card acceptance locations, via the card reader interface device. The SCPS 330 must determine which concessions and

loyalty programs/parameters should go on the smart cards, and monitor for any changes effected by the CHAPS 310.

The transaction processor 340 is responsible for rating the transactions as received from the front office. For each concession and loyalty program granted  
5 the cardholder and account owner, the transaction processor 340 may, for each transaction, price the transaction at full price/fare, at a reduced price/fare, or refund a part of or the whole price/fare.

The configuration manager 350 is responsible for combining the generated concession and loyalty lists with other card acceptance location related  
10 configuration data and forwarding the configuration data, including the generated lists, to the correct card reader interface device. As described above in the preferred embodiment, the card reader interface device is used to facilitate data communications with the card acceptance locations which may be a mobile location, such as a bus or train, and connected to the rest of the system in an off-  
15 line mode, or may be a fixed location, such as a retail store, and connected to the rest of the system in an on-line mode.

The card acceptance locations are responsible for creating the smart card transactions, and forwarding these transactions to the card reader interface device that in turn forwards them to the CHAPS 310 for concession and loyalty  
20 processing that is required for the settlement and clearing of these transactions. In some cases, the card acceptance locations may forward these transactions directly to the CHAPS 310.

Smart card transactions include regular debit transactions for usage that this card acceptance location has accrued during the operational day use, as well  
25 as smart card concession/loyalty update transactions. The concession/loyalty update transactions serve the purpose to indicate to the CHAPS 310 that a smart card has been updated with the latest concessions. This allows the CHAPS 310 to purge the UID of the smart card from the concession list. This keeps the concession list size down to a minimum, and stops the list from growing without  
30 bound.

On either a periodic or on-demand basis, the CHAPS 310 reviews user eligibility for concessions and loyalty programs based on the criteria dictated by the service provider, system operator, and/or system owner. Likewise, for systems where the concessions and loyalty program/parameters are stored on the card, the CHAPS 310 must be capable of generating list(s) containing all cards that had a change of concessions, loyalty programs, or loyalty program parameters, based on the criteria dictated by the service provider. Once these lists are generated, they are combined with card acceptance location configuration/operational data (if any exists) and are routed to the destination card acceptance locations. The card acceptance locations acknowledge successful receipt of the lists, and no further attempts are made by the system 300 to transmit the lists to these particular card acceptance locations. Once a change is made to the concessions and loyalty programs, the transaction processor 340 will consider the new concessions and/or loyalty programs/parameters in determining the price of the service/product purchased by the cardholder. Any updates to the smart card concession status, loyalty programs, or loyalty program parameters are made to the smart card during the presentation of the smart card to the card acceptance location. Any new transactions effected by the cardholder will incorporate the new concessions and loyalty programs.

FIGS. 6A and 6B illustrate a flowchart of the alternative embodiment of the present invention depicting loyalty and concessions processing. Processing begins 401 within a back office system 400 that comprises one or more computer systems employing one or more databases that monitor 402 the concession and loyalty parameters of the smart cards in the system. For each card, the back office system 400 determines 403 whether a loyalty or concession parameter should be updated on the smart card. If no parameter update is required, the next card is processed 404. A person of ordinary skill in the art can readily appreciate that a transaction list can drive the selection of cards selected for parameter update, rather than selecting cards sequentially by the UID of the smart card.



If the back office system 400 determines 403 that a smart card requires concession/loyalty parameter update, the back office system 400 maps 405 the UID of the smart card to an associated reader interface device for later transmission 411 of information to the card acceptance location 423. This mapping may occur at any step between step 403 and step 411.

If the back office system 400 determines 406 that the card needs to be updated by adding a parameter to the card, it places 407 the UID of the smart card on the appropriate loyalty/concession "add" list. If the back office system 400 determines 408 that the smart card needs to be updated by removing a parameter from the smart card, it places 409 the UID of the smart card on the appropriate loyalty/concession "remove" list. The pair of steps 406, 407 may be interchanged with the pair 408, 409 without changing the transmission 411 of data from the back office system 400 to the card acceptance location 423.

If smart cards or transactions remain 410 unprocessed that would update loyalty/concession parameters on the smart cards, they are processed beginning at step 404, and proceeding to steps 402, 403, 404, 405, 406, 407, 408, 409 and 410. When the back office system 400 has processed 410 all cards and/or transactions that require loyalty/concession parameter updates to the smart cards, it transmits 411 the "add" list created in step 407 and the "remove" list created in step 409 to the card acceptance locations 423, via any existing card reader interface devices, as determined at step 405.

Upon receiving the "add" and "remove" lists, the card acceptance location stores 412 the lists in its memory and acknowledges their receipt and storage 412 to the back office system 400. The card acceptance location then processes each smart card presented to it.

The card acceptance location queries 413 the stored lists to determine whether a presented smart card is on a loyalty/concession "add" list. If the presented card is on an "add" list, the card acceptance location issues a command 414 to the smart card to update the loyalty/concession parameter on the smart

card. The card acceptance location records 415 the update in memory as a loyalty/concession transaction.

The card acceptance location 423 queries 416 the stored lists to determine whether a presented smart card is on a loyalty/concession "remove" list. If the presented smart card is on a "remove" list, the card acceptance location 423 issues a command 417 to the smart card to remove the loyalty/concession parameter from the smart card. The card acceptance location 423 records 418 the update in memory as a loyalty/concession transaction. Depending on business rules governing the order of processing "add" and "remove" loyalty/concession transactions, the steps 413, 414 and 415 may be interchanged with steps 416, 417 and 418.

If the card acceptance location 423 is at the end of its service period 419, it transmits 420 all transactions created during its service period to the back office system 400. If the card acceptance location 423 is not at the end of its service period 419, it continues to process presented smart cards as in steps 413, 414, 415, 416, 417 and 418. The back office system 400 purges 421 the UID of the smart card from its loyalty/concession "add" and "remove" lists based on the transactions recorded by the card acceptance location 423 in steps 415 and 418. When the card acceptance location 423 has transmitted 420 its transactions to the back office system 400, it ends 422 processing of loyalty/concession transactions until the next service period.

FIG. 7 illustrates a bounce diagram of regulating concession eligibility in accordance with the alternative embodiment of the present invention. In light of the above description of the alternative embodiment, FIG. 7 is self-explanatory and will not be discussed in detail.

While the invention has been described in conjunction with specific embodiments thereof, additional advantages and modifications will readily occur to those skilled in the art. The invention, in its broader aspects, is therefore not limited to the specific details, representative apparatus, and illustrative examples shown and described. Various alterations, modifications and variations will be

apparent to those skilled in the art in light of the foregoing description. For example, the smart card system in the various embodiments may have more or less system components, or the components may perform different functions. The smart card systems may have a broad range of applications that they can be used for. These may include, but certainly not limited to, access control, medical record applications, banking, currency replacement systems, transit or mobility, secure access to the intranet and internet, and the like. Thus, it should be understood that the invention is not limited by the foregoing description, but embraces all such alterations, modifications and variations in accordance with the spirit and scope of the appended claims.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221